

AMAX keypad 3000 L8

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Single button arming of alarm system
- ▶ Fire, medical and panic alarms
- ▶ Tamper switch
- ▶ Stylish and modern design
- ▶ Easy to use

The AMAX keypad 3000 L8 is an 8-zone LED keypad, that is compatible with all AMAX panels. Easy to recognize icons display system conditions in a simple to view format. Zone status is indicated numerically across the top of the screen.

The codepad notifies you when a zone is open, when there has been an alarm, and in which zone the alarm has occurred.

Functions

Arming methods

You can arm the system by entering your Code and pressing the [# / *] key, or quick arm the system by holding down the [# / *] key for 2 sec.

There are two options to arm the system:

- To arm the system and stay, press [*].
- To arm the system and leave the house, press [#].

Keypad areas

Up to 16 AMAX keypads can be connected on one AMAX panel.

LED keypads can be assigned to one area.

Fire, Medical and Panic alarms

If programmed to do so, simultaneously pressing the outside buttons of a row on any code pad, an alarm report is sent to the Central Monitoring Station. Press

[4] and [6] simultaneously for a fire alarm; press [7] and [9] simultaneously for a medical alarm; and press [1] and [3] or [*] and [#] simultaneously for a panic alarm.

Certifications and approvals

| Region | Certification | |
|---------|---------------|---|
| Europe | CE | DIN EN 50130-4 (6/2011) DIN EN 55022 (5/2008) EN 60950-1:2006 + A11:2009 + A1:2010 |
| | EN | 50131-3 Grade 2, Environmental Class II |
| Germany | VdS | A |

Technical specifications

Enclosure Design

| | |
|-------------|-----------------------------|
| Dimensions: | • 138 x 115 x 24 mm (LxWxH) |
| Weight: | • 254g |
| Color: | • White |

Environmental Considerations

| | |
|-----------------------|------------------|
| Operating Temperature | • -10°C to +55°C |
|-----------------------|------------------|

| | |
|-------------------|--------------|
| Relative Humidity | • 10% to 95% |
|-------------------|--------------|

Power Requirements

| | |
|----------------------|----------------------|
| Input Voltage range: | • 10.8VDC to 13.8VDC |
|----------------------|----------------------|

| | |
|----------------------|----------------------------|
| Current Consumption: | • standby 31mA , max. 60mA |
|----------------------|----------------------------|

| | |
|---------------------|---|
| Cable requirements: | <ul style="list-style-type: none"> • four wire, AWG18 or AWG22 • maximum length 200m (Panel to last KP) • maximum BUS 1 length 700m (max 14 devices, max 8 KPs) • maximum BUS 2 length 700m (max 14 devices, max 8 KPs) |
|---------------------|---|

| | |
|----------|-----|
| EN Type: | • B |
|----------|-----|

Ordering information**AMAX keypad 3000 L8**

AMAX keypad 3000 L8 is a 8 zone LED keypad

Approval: EN 50131-3 Grade2

Order number **IUI-AMAX3-LED8**

Represented by:**Americas:**

Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com