

AMAX keypad 4000 T

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Simple Icons for system condition
- ▶ Quick menu programming
- ▶ Fire, medical and panic alarms
- ▶ Zone input, on Board
- ▶ Event log on Display

The AMAX keypad 4000 T is a LCD Text keypad that is compatible with the AMAX panel 4000 / AMAX panel 4000 EN.

Up to 16 Text keypads can be connected to one AMAX 4000 panel. Text Keypads can be used as Master Keypads for different areas.

Text Keypads are Multilingual Keypads.

Functions

Arming methods

You can arm the system by entering your Code and pressing the [# / *] key, or quick arm the system by holding down the [# / *] key for 2 sec.

There are two options to arm the system:

- To arm the system and stay, press [*].
- To arm the system and leave the house, press [#].

Text keypad languages

Several languages can be displayed on the Text Keypad. The languages are based on the AMAX panel 4000 Software package.

There are three packages available:

- for AMAX panel 4000:
 - **SW Language package 1:** English, Polish
- for AMAX panel 4000 EN:
 - **SW Language package 2:** French, Italian, German, Dutch
 - **SW Language package 3:** English, Spanish, Swedish, Polish

- **SW Language package 3:** English, Spanish, Swedish, Polish

Fire, Medical and Panic alarms

If programmed to do so, simultaneously pressing the outside buttons of a row on any code pad, an alarm report is sent to the Central Monitoring Station. Press [4] and [6] simultaneously for a fire alarm; press [7] and [9] simultaneously for a medical alarm; and press [1] and [3] or [*] and [#] simultaneously for a panic alarm.

Certifications and approvals

Region	Certification	
Europe	CE	DIN EN 50130-4 (6/2011) DIN EN 55022 (5/2008) EN 60950-1:2006 + A11:2009 + A1:2010
	EN	50131-3 Grade 2, Environmental Class II
Germany	VdS	A

Technical specifications

Enclosure Design

Dimensions:	<ul style="list-style-type: none"> 138 x 115 x 24 mm (LxWxH)
Weight:	<ul style="list-style-type: none"> 254g
Color:	<ul style="list-style-type: none"> White

Environmental Considerations

Operating Temperature	<ul style="list-style-type: none"> -10°C to +55°C
Relative Humidity	<ul style="list-style-type: none"> 10% to 95%

Power Requirements

Input Voltage range:	<ul style="list-style-type: none"> 10.8VDC to 13.8VDC
Current Consumption:	<ul style="list-style-type: none"> standby 31mA, max. 100mA
Cable requirements:	<ul style="list-style-type: none"> four wire, AWG18 or AWG22 maximum length 200m (Panel to last KP) maximum BUS 1 length 700m (max 14 devices, max 8 KPs) maximum BUS 2 length 700m (max 14 devices, max 8 KPs)
EN Type:	<ul style="list-style-type: none"> B

Ordering information

AMAX keypad 4000 T

AMAX keypad 4000 T is a Text keypad

Approval: EN 50131-3 Grade2

Order number **IUI-AMAX4-TEXT**

Represented by:

Americas:

Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com