



The WRMT is a multi-functional remote control that allows a user to interact with their acre intrusion system. The device supports common functions such as Set, Unset and Partset as well as a user programmable output function and a panic/SOS feature. The WRMT battery is also replaceable.

Key Features

- Easy to pair and easy to remove from acre intrusion system
- Intuitive LED behavior provides system status feedback
- Configurable 'Function' button – can be assigned to activate an output (e.g. Garage Door), or to trigger an acre intrusion setting procedure.
- Panic/SOS functionality (Dual button press)

Technical Data

Power And Mechanical

Battery type	3V Li CR2032
Operating temperature	-10 ~ +50 °C

Intrusion

Event transmission	Set, unset, partset, configurable function, panic/SOS, low battery
--------------------	--

General

Battery life	> 3 years
Current consumption	Standby <1 µA Transmission ~30 mA
Dimensions (L x W x H)	55 x 28 x 12mm
Frequency	868-869Mhz
Range	up to 300m in open air
Weight	20g

Ordering Data

Type	Article reference	Description
WRMT	V54543-F117-A300	WRMT Wrls Remote Control with 4 Buttons